

Control Box CF11H

CF11H control box is designed for furniture application. It is able to drive up to 2 actuators. With internal SMPS, CF11H features lightweight and compact dimension for convenient installation. Moreover, it is compatible with wide range of Moteck mainstream actuators and handsets products.




Features

- Main applications: Furniture
- Input: 100 ~ 240V AC, 50/60Hz (SMPS)
- Output: 29V DC
- Power supply: Internal SMPS, 29V DC/2A (58W)
- Overload protection current: 3.6A (per channel)
- Max. number of actuators: 2 channels
- Max. number of controls: 1 channel
- Duty cycle: 10%, max. 2 min. continuous operation in 20 min.
- Electric shock protection level: Class II
- Color: Black
- Power cord: Refer to AC Power Cord

1

Dimensions



Unit: mm

I/O Introduction




Compatibility

Product	Model	Compatible requirement		
Actuator	BD61, BD62, FD40, FD60, FD61, GD70, MK33	Without positioning sensor With Moteck L3-type minifit 6-pin plug		
Hand control	HD, HJ, HM, H2N, H3F, H3NT	Moteck P1 control category With Moteck E2-type RJ 10-pin plug		

Socket

• Motor socket for Moteck L3-type minifit plug



Minifit 6-pin Socket

Note: Connect M+ to "Vdc +" & M- to "Vdc -" of DC power to extend the motor. Switch the polarity of DC input to retract it.

• Hand control socket for Moteck E2-type RJ plug



RJ 10-pin Socket





• AC Power cord

Code				
Plug type	AC Power cord length		Connector type	
(plug in the wall)	2000mm straight	3000mm straight	(plug in the control box)	
US 2-Pin Plug			IEC 60320 C7 type connector	
	A2	А3		
			4555	
EU 2-Pin Plug				
	C2	С3		
CEE 7/17(VDE) 2-Pin Plug				
		V3		
UK 3-Pin Plug				
		G3		

